




EventLITE 4/10 Q6

Product code: 44067

Preface

Thank you for purchasing this Showtec product.

The purpose of this user manual is to provide instructions for the correct and safe use of this product.

Keep the user manual for future reference as it is an integral part of the product. The user manual shall be stored at an easily accessible location.

This user manual contains information concerning:

- Safety instructions
- Intended and non-intended use of the device
- Installation and operation of the device
- Maintenance procedures
- Troubleshooting
- Transport, storage and disposal of the device

Non-observance of the instructions in this user manual may result in serious injuries and damage of property.

©2025 Showtec. All rights reserved.

No part of this document may be copied, published or otherwise reproduced without the prior written consent of Highlite International.

Design and product specifications are subject to change without prior notice.

For the latest version of this document or other language versions, please visit our website www.highlite.com or contact us at service@highlite.com.

Highlite International and its authorized service providers are not liable for any injury, damage, direct or indirect loss, consequential or economic loss or any other loss arising from the use of, or inability to use or reliance on the information contained in this document.

Highlite International B.V. – Vestastraat 2 – 6468 EX Kerkrade – the Netherlands

Table of contents

1. Introduction.....	4
1.1. Before Using the Product.....	4
1.2. Intended Use.....	4
1.3. LEDs Lifespan.....	4
1.4. Text Conventions.....	4
1.5. Symbols and Signal Words.....	5
1.6. Symbols on the Information Label.....	5
2. Safety.....	6
2.1. Warnings and Safety Instructions.....	6
2.2. Requirements for the User.....	7
3. Description of the Device.....	8
3.1. Front View.....	8
3.2. Bottom View.....	8
3.3. Product Specifications.....	9
3.4. Dimensions.....	10
3.5. Optional Accessories.....	10
4. Installation.....	11
4.1. Safety Instructions for Installation.....	11
4.2. Personal Protective Equipment.....	11
4.3. Installation Site Requirements.....	11
4.4. Mounting Options.....	12
4.4.1. Upright Installation.....	12
4.4.2. Installation with a Clamp.....	12
4.5. Charging the Battery.....	13
4.5.1. Battery LED Indicator Statuses.....	13
5. Setup.....	14
5.1. Stand-alone Setup.....	14
5.2. DMX Connection	14
5.2.1. DMX-512 Protocol.....	14
5.2.2. DMX Cables.....	14
5.2.3. Master/Slave Setup.....	15
5.2.4. DMX Linking.....	15
5.2.5. DMX Addressing.....	16
5.3. Wireless Connection.....	17
5.3.1. Wireless Master/Slave Setup.....	17
5.3.2. Setup with a Controller.....	18
6. Operation.....	19
6.1. Safety Instructions for Operation.....	19
6.2. Control Modes.....	19
6.3. Control Panel.....	19
6.4. Switching ON/OFF.....	20
6.5. Start-up.....	20
6.6. Menu Overview.....	21
6.7. Main Menu Options.....	22
6.7.1. DMX.....	22
6.7.1.1. Signal.....	23
6.7.1.2. WDMX Unlock.....	23
6.7.2. Manual.....	23
6.7.3. Frequency.....	24
6.7.4. Auto.....	24
6.7.5. Program.....	24
6.7.6. Slave.....	25
6.7.7. Working Time.....	25
6.7.8. Settings.....	25
6.7.8.1. DMX Fail.....	26
6.7.8.2. Lock.....	26
6.7.8.3. Factory Reset.....	26

6.7.9. Information.....	26
6.8. Remote Control.....	27
6.8.1. Remote Control Mode.....	27
6.8.2. Functions of the Remote Control Buttons.....	28
6.9. DMX Channels.....	29
7. Troubleshooting.....	30
8. Maintenance.....	31
8.1. Preventive Maintenance.....	31
8.1.1. Basic Cleaning Instructions.....	31
8.2. Corrective Maintenance.....	31
9. Deinstallation, Transportation and Storage.....	31
9.1. Instructions for Deinstallation.....	31
9.2. Instructions for Transportation.....	32
9.3. Storage.....	32
10. Disposal.....	32
11. Approval.....	32

1. Introduction

1.1. Before Using the Product

**Important**

Read and follow the instructions in this user manual before installing, operating or servicing this product.


The manufacturer will not accept liability for any resulting damages caused by the non-observance of this manual.

After unpacking, check the contents of the box. If any parts are missing or damaged, contact your Highlite International dealer.

Your shipment includes:

- Showtec EventLITE 4/10 Q6
- Schuko to IEC power cable (1,5 m)
- User manual

Figure 1



1.2. Intended Use

This device is intended for professional use as a battery-powered spotlight. It can be installed indoors and outdoors. This device is not suitable for households and for general lighting.

Any other use, not mentioned under intended use, is regarded as non-intended and incorrect use.

1.3. LEDs Lifespan

The light output of the LEDs gradually decreases over time (lumen depreciation). High operating temperatures contribute to this process. You can extend the lifespan of the LEDs by providing adequate ventilation and operating the LEDs at the lowest possible brightness.

1.4. Text Conventions

Throughout the user manual the following text conventions are used:

- Buttons: All buttons are in bold lettering, for example "Press the **UP/DOWN** buttons"
- References: References to parts of the device are in bold lettering, for example: "turn the **adjustment handle (05)**". References to chapters are hyperlinked
- 0–255: Defines a range of values
- Notes: **Note:** (in bold lettering) is followed by useful information or tips

1.5. Symbols and Signal Words

Safety notes and warnings are indicated throughout the user manual by safety signs.

Always follow the instructions provided in this user manual.

**DANGER**

Indicates an imminently hazardous situation which, if not avoided, will result in death or serious injury.

**WARNING**

Indicates a potentially hazardous situation which, if not avoided, could result in death or serious injury.

**CAUTION**

Indicates a potentially hazardous situation, which, if not avoided, may result in minor or moderate injury.

**Attention**

Indicates important information for the correct operation and use of the product.

**Important**

Read and observe the instructions in this document.

**Electrical hazard**

Provides important information about the disposal of this product.

1.6. Symbols on the Information Label

This product is provided with an information label. The information label is located on the base plate of the device.

The information label contains the following symbols:



This device shall not be treated as household waste.



Read and follow the instructions in the user manual before installing, operating or servicing the device.



Do not stare at the light source.

2. Safety

**Important**

Read and follow the instructions in this user manual before installing, operating or servicing this product.

The manufacturer will not accept liability for any resulting damages caused by the non-observance of this manual.

2.1. Warnings and Safety Instructions

**DANGER**

Danger for children

For adult use only. The device must be installed beyond the reach of children.

- Do not leave any parts of the packaging (plastic bags, polystyrene foam, nails, etc.) within the reach of children. Packaging material is a potential source of danger for children.

**DANGER**

Risk of explosion caused by incorrect handling

This device contains a built-in rechargeable lithium-ion battery. The battery is not replaceable. The battery may explode or cause burns if it is crushed, disassembled or exposed to fire or high temperatures.

- Do not open the device and do not attempt to remove the built-in battery.
- Do not disassemble the battery.
- Do not crush or puncture the battery.
- Do not short-circuit the battery.
- Do not expose the battery to water or other liquids.
- Keep the battery away from fire and heat.

**WARNING**

Risk of epileptic shock

Strobe lighting can trigger seizures in photosensitive epilepsy. Sensitive persons should avoid looking at strobe lights.

**Attention**

Power supply

This device has a built-in AC power adapter that is used to charge the battery.

Before connecting the device to the power supply, make sure that the current, voltage and frequency match the input voltage, current and frequency specified on the information label on the device.

**Attention**

General safety

- Do not connect the device to a dimmer pack.
- Do not switch the device on and off in short intervals. This reduces the device's life.

- Do not shake the device. Avoid brute force when installing or operating the device.
- Change the lens or the LEDs if they are visibly damaged to such an extent that their effectiveness is impaired, for example by cracks or deep scratches. Contact your Highlite International dealer for more information, as servicing can be performed only by instructed or skilled persons.
- If the device is dropped or struck, disconnect the device from the electrical power supply immediately.
- If the device is exposed to extreme temperature variations (e.g. after transportation), do not switch it on immediately. Let the device reach room temperature before switching it on, otherwise it may be damaged by the formed condensation.
- If the device fails to work properly, discontinue use immediately.



Attention
For professional use only
This device must be used only for the purposes it is designed for.

This device is intended for professional use as a battery-powered spotlight. Any incorrect use may lead to hazardous situations and result in injuries and material damage.

- This device is not suitable for households and for general lighting.
- This device is not designed for permanent operation.
- This device does not contain user-serviceable parts. Unauthorized modifications to the device will render the warranty void. Such modifications may result in injuries and material damage.



Attention
Before each use, examine the device visually for any defects.

Make sure that:

- All screws used for installing the device or parts of the device are tightly fastened and are not corroded.
- The safety devices are not damaged.
- There are no deformations on housings, fixings and installation points.
- The lens is not cracked or damaged.
- The power cables are not damaged and do not show any material fatigue.



Attention
Do not expose the device to conditions that exceed the rated IP class conditions.

The top part of the device is IP54 rated. The bottom part of the device is IP20 rated. IP (Ingress Protection) 54 class provides protections against dust and water splashes. IP (Ingress Protection) 20 class provides protection against solid objects greater than 12 mm, such as fingers, and no protection against harmful ingress of water.

2.2. Requirements for the User

This product may be used by ordinary persons. Maintenance may be carried out by ordinary persons. Installation and service shall be carried out only by instructed or skilled persons. Contact your Highlite International dealer for more information.

Instructed persons have been instructed and trained by a skilled person, or are supervised by a skilled person, for specific tasks and work activities associated with the installation, service and maintenance of this product, so that they can identify risks and take precautions to avoid them.

Skilled persons have training or experience, which enables them to recognize risks and avoid hazards associated with the installation, service and maintenance of this product.


Ordinary persons are all persons other than instructed persons and skilled persons. Ordinary persons include not only users of the product but also any other persons that may have access to the device or who may be in the vicinity of the device.

3. Description of the Device

The Showtec EventLITE 4/10 Q6 is a battery-powered RGBWAUV spot with wireless DMX. The device can be tilted 25°, which is useful to uplight a wall. It includes automated programs, can be daisy-chained in master/slave mode (wired and wireless DMX), and can be operated manually by optional IR-remote controller and by (wireless) DMX.

3.1. Front View


Figure 2



- 01) Wireless DMX receiving antenna
- 02) Carrying handle
- 03) IR sensor
- 04) Battery LED indicator
- 05) 4 x 10 W RGBWAUV LEDs
- 06) Anti-theft lock hole (for laptop lock)
- 07) Safety eye
- 08) Mounting hole (M10)

3.2. Bottom View

Figure 3



- 09) Latch
- 10) Push button switch (ON/OFF)
- 11) Control panel: OLED display and touch buttons
- 12) Wireless LED indicator
- 13) Ground/Earth connection
- 14) 3-pin DMX signal connector IN
- 15) 3-pin DMX signal connector OUT
- 16) IEC power connector IN, 100–240 V AC, 50/60 Hz, with a self-closing cover
- 17) Support bracket

3.3. Product Specifications

Model:	EventLITE 4/10 Q6
Source:	
Light source type	LED
Light source quantity	4
Light source power	40 W
LED color type	RGBWAUV
Refresh rate	25000 Hz
Luminous flux (total)	1050 lm
Optical:	
Beam angle (circular)	15°
Battery:	
Battery type	Lithium ion
Battery voltage	14,8 V
Capacity	5,2 Ah
Runtime @full	5 h
Charging time	10 h
Control and Programming:	
Control mode	DMX / Manual / Master Slave / Remote / Stand Alone
DMX channels	6 / 8 / 11
Protocols	DMX / W-DMX
Wireless	Wireless DMX
Carrier frequency	2,4 GHz
Display	OLED
Dynamic Effects:	
Dimmer	0–100 %
Electrical Specifications and Connections:	
Power supply	100–240 V AC 50/60 Hz
Power consumption	45 W
Power connector IN	IEC
DMX connector IN	XLR 3P
DMX connector OUT	XLR 3P
AC Power Adapter (built-in):	
Input voltage	100–240 V AC 50/60 Hz
Input current	1,5 A
Output voltage	17,1 V DC
Output current	1,8 A
Mechanical Specifications:	
Length	140 mm
Width	140 mm
Height	205 mm
Weight	3,2 kg
IP rating	IP20 Rear / IP54
Housing	Metal

Color	Black
-------	-------

Product Properties:

Cooling	Convection
---------	------------


Thermal Specifications:

Maximum ambient temperature	40 °C
Minimum ambient temperature	-10 °C

Included Items:

Included cables	IEC cable
-----------------	-----------

3.4. Dimensions

Figure 4


3.5. Optional Accessories

The following optional accessories are available for this product:

- [44062](#) IR Remote for EventLITE 4/10
- [44063](#) Carrying Bag for 4 x EventLITE 4/10
- [44064](#) Charger Case for 6 x EventLITE 4/10
- [44065](#) Chrome Cover for EventLITE 4/10
- [44066](#) White Cover for EventLITE 4/10

Contact your Highlite International dealer for more information.

4. Installation

4.1. Safety Instructions for Installation

**WARNING**

Incorrect installation can cause serious injuries and damage of property.

If trussing systems are used, installation must be carried out only by instructed or skilled persons.

Follow all applicable European, national and local safety regulations concerning rigging and trussing.

4.2. Personal Protective Equipment

During installation, deinstallation and rigging wear personal protective equipment in compliance with the national and site-specific regulations.

4.3. Installation Site Requirements

- The device can be used indoors and outdoors.
- The device must be installed away from heating sources and direct sunlight.
- The ambient temperature must be in the range -10 and 40 °C.

**Attention**

Do not expose the device to conditions that exceed the rated IP class conditions.

The top part of the device is IP54 rated. The bottom part of the device is IP20 rated. IP (Ingress Protection) 54 class provides protections against dust and water splashes. IP (Ingress Protection) 20 class provides protection against solid objects greater than 12 mm, such as fingers, and no protection against harmful ingress of water.

4.4. Mounting Options

The device can be positioned on a flat surface or mounted to a truss or other rigging structure in any orientation. Make sure that all loads are within the pre-determined limits of the supporting structure.



CAUTION

Restrict the access under the work area during installation.

4.4.1. Upright Installation

Place the device on a flat surface.

You can tilt the device at a maximum angle of 25° to light up an object. To tilt the device, follow the steps below:

- 01) Press the **latch (09)** to release the **support bracket (17)**.
- 02) While you keep the **latch (09)** pressed, adjust the angle of the **support bracket (17)**. The adjustment range is 0°–25°.
- 03) Release the **latch (09)** to lock the **support bracket (17)** in position.


Figure 5



4.4.2. Installation with a Clamp

- 01) Use a clamp to attach the device to the supporting structure.
- 02) Secure the device with a secondary suspension, for example a safety cable. Make sure that the secondary suspension can hold 10 times the weight of the device. Put the safety cable through the **safety eye (07)**.

Figure 6



4.5. Charging the Battery



DANGER
Risk of explosion caused by incorrect handling


This device contains a built-in rechargeable lithium-ion battery. The battery is not replaceable. The battery may explode or cause burns if it is crushed, disassembled or exposed to fire or high temperatures.

- Do not open the device and do not attempt to remove the built-in battery.

To charge the battery follow the steps below:

- 01) Turn off the device from the **push button switch (10)**.
- 02) Connect the device to power supply with the delivered IEC power cable. The **battery LED indicator (04)** lights up red. When charging is completed the **battery LED indicator (04)** lights up green.

During charging the display shows the state of charge of the battery and the battery charging symbol:



- Charge the battery before using the device for the first time.
- Do not deep discharge the battery as this will shorten the lifespan of the battery. Recharge the battery as soon as possible. Do not let the light run until the battery is depleted.
- Make sure that the battery is charged to at least 50 % before storing the device.

It is recommended to charge the device at an ambient temperature between 0 and 35 °C.

If the device is charged in a carrying case, leave the case open.

Refer to the product specifications (see [3.3. Product Specifications](#) on page 9) for the charge time of the battery.

Note:

There is a charging case available for this product (see [3.5. Optional Accessories](#) on page 10). It can accommodate up to 6 devices EventLITE 4/10 Q6.

4.5.1. Battery LED Indicator Statuses

The device has a **battery LED indicator (04)** that shows the charge state of the battery:

LED color		LED behavior	State of charge
	Yellow	Flashing	< 30 %
	Red	Lights up	charging
	Green	Lights up	fully charged

5. Setup

5.1. Stand-alone Setup

When the EventLITE 4/10 Q6 is not connected to a controller or to other devices, it functions as a stand-alone device. It can be operated manually via the control panel or with an IR remote control.

For more information refer to Control Modes (see [6.2. Control Modes](#) on page 19).

5.2. DMX Connection

5.2.1. DMX-512 Protocol

You need a DMX serial data link to run light shows of one or more devices using a DMX-512 controller or to run synchronized shows of 2 or more devices in master/slave control mode.

The EventLITE 4/10 Q6 has 3-pin DMX signal IN and OUT connectors.

The pin assignment is as follows: pin 1 (ground), pin 2 (-), pin 3 (+).

Devices on a serial data link must be daisy-chained in a single line. The number of devices that you can control on one data link is limited by the combined number of the DMX channels of the connected devices and the 512 channels available in one DMX universe.

To comply with the TIA-485 standard, no more than 32 devices should be connected on one data link. In order to connect more than 32 devices on one data link, you must use a DMX optically isolated splitter/booster, otherwise this may result in deterioration of the DMX signal.

Note:

- Maximum recommended DMX data link distance: 300 m
- Maximum recommended number of devices on a DMX data link: 32 devices


5.2.2. DMX Cables

Shielded twisted-pair cables with 3-pin XLR connectors must be used for reliable DMX connection. You can purchase DMX cables directly from your Highlite International dealer or make your own cables.

If you use XLR audio cables for DMX data transmission, this may lead to signal degradation and unreliable operation of the DMX network.

When you make your own DMX cables, make sure that you connect the pins and wires correctly as shown in the figure below.

Figure 7




5.2.3. Master/Slave Setup

The EventLITE 4/10 Q6 supports master/slave control mode. To connect multiple devices in a master/slave setup, follow the steps below:

- 01) Connect the DMX OUT connector of the 1st device to the DMX IN connector of the 2nd device with a 3-pin DMX cable.
- 02) Repeat step 1 to connect all devices in a daisy-chain.
- 03) Connect a DMX terminator (120 Ω resistor) to the DMX OUT connector of the last device on the data link.
- 04) Set the 1st device on the data link as a master device (see [6.7.6. Slave](#) on page 25).
- 05) Set the remaining devices as slave devices (see [6.7.6. Slave](#) on page 25).

Figure 8




5.2.4. DMX Linking

To connect multiple devices on one DMX data link, follow the steps below:

- 01) Use a 3-pin DMX cable to connect the DMX OUT connector of the lighting controller to the DMX IN connector of the 1st device.
- 02) Connect the DMX OUT connector of the 1st device to the DMX IN connector of the 2nd device with a 3-pin DMX cable.
- 03) Repeat step 2 to connect all devices in a daisy-chain.
- 04) Connect a DMX terminator (120 Ω resistor) to the DMX OUT connector of the last device on the data link.

Figure 9



5.2.5. DMX Addressing

In a setup with multiple devices, make sure that you set the DMX starting address of each device correctly. The EventLITE 4/10 Q6 has 3 personalities: 11 channels, 8 channels, and 6 channels.

If you want to connect multiple devices on one data link and use them in 11-channel mode, for example, follow the steps below:

- 01) Set the starting address of the 1st device on the data link to 1 (001).
- 02) Set the starting address of the 2nd device on the data link to 12 (012), as $1 + 11 = 12$.
- 03) Set the starting address of the 3rd device on the data link to 23 (023), as $12 + 11 = 23$.
- 04) Continue assigning the starting addresses of the remaining devices by adding 11 each time to the previous number.

When addressing multiple devices on one data link, make sure that there are no overlapping channels. You cannot control devices individually if they have overlapping channels.

5.3. Wireless Connection

The EventLITE 4/10 Q6 has a built-in wireless transceiver. You can pair the device with other EventLITE 4/10 Q6 devices in a master/slave setup or with an LED controller with a wireless transmitter in DMX control mode. If the LED controller is not equipped with a wireless transmitter, you can connect the LED controller to a wireless DMX transceiver.

Note:

The maximum wireless transmission range is 350 m.


Make sure that there is a clear line of sight between all devices in the wireless setup.

5.3.1. Wireless Master/Slave Setup

To connect multiple devices in a wireless master/slave setup, follow the steps below:

- 01) Set one of the devices in the setup as a master device (see [6.7.6. Slave](#) on page 25).
- 02) Set the remaining devices as slave devices (see [6.7.6. Slave](#) on page 25).
- 03) Configure all devices to receive wireless DMX (see [6.7.1.2. WDMX Unlock](#) on page 23).
- 04) Pair the master device with the slave devices (see [6.7.1.1. Signal](#) on page 23). During pairing, the **wireless LED indicator (12)** blinks. When pairing is completed, the **wireless LED indicator (12)** lights up.

Figure 10



Note:

Once a slave device is paired to a master device in a wireless master/slave setup, the slave device remains paired to the master device. If you want to use the slave device in a different master/slave setup, you need to unpair the slave device from the first master device (see [6.7.1.1. Signal](#) on page 23).


5.3.2. Setup with a Controller

To pair multiple devices to an LED controller with wireless DMX, follow the steps below:

- 01) Set all devices in the setup as slave devices (see [6.7.6. Slave](#) on page 25).
- 02) Configure all devices to receive wireless DMX (see [6.7.1.2. WDMX Unlock](#) on page 23).
- 03) Pair the devices with the LED controller. Refer to the user manual of the LED controller for more information.

During pairing, the **wireless LED indicator (12)** blinks. When pairing is completed, the **wireless LED indicator (12)** lights up.

Figure 11



6. Operation

6.1. Safety Instructions for Operation



Attention

This device must be used only for the purposes it is designed for.

This device is intended for professional use as a battery-powered spotlight. It can be installed indoors and outdoors. This device is not suitable for households and for general lighting.

Any other use, not mentioned under intended use, is regarded as non-intended and incorrect use.

6.2. Control Modes

The EventLITE 4/10 Q6 can be controlled:

- manually (see [6.7. Main Menu Options](#) on page 22)
- via IR remote control (see [6.8. Remote Control](#) on page 27)
- via DMX (see [6.9. DMX Channels](#) on page 29)

It supports a master/slave connection and is equipped with a wireless transceiver.


This table shows the different control options and the available features for each control mode.

	Manual	IR Remote	(Wireless) DMX-512
Auto Mode	yes	yes	yes
Built-in programs	yes	yes	yes
Custom colors	yes	no	yes
Manual	yes	yes	yes

For more information about how to connect the device to an LED controller and to other devices, refer to Setup (see [5. Setup](#) on page 14).

6.3. Control Panel

Figure 12



- Use the **MENU** button to exit the current submenu, to return to the Main Menu and to return to the start screen.
- Use the **UP/DOWN** buttons to navigate through the menus or to increase/decrease numeric values.
- Use the **ENTER** button to open the desired menu, to confirm your choice or to set the currently selected value.

6.4. Switching ON/OFF

The device has a power switch.




- Press the **push button switch (10)** into ON position to switch on the device.
- Press the **push button switch (10)** into OFF position to switch off the device.

Make sure that the device is switched off from the **push button switch (10)** when the device is not in use.

6.5. Start-up

At start-up the display shows a splash screen with the Showtec logo followed by the start screen:



The start screen provides information about the selected DMX channel mode, the DMX starting address of the device, the state of the battery, and the temperature of the LEDs. During charging, the display shows the battery charging symbol.

Note:

If no button is pressed, after 30 s of inactivity the display turns off. Press any button to turn the display on. You can change this setting in the Backlight Time submenu (see [6.7.8. Settings](#) on page 25).

6.6. Menu Overview

Level 1	Level 2	Level 3
DMX (see 6.7.1. DMX on page 22)	Address	000-512
	Channel	6
		8
		11
	Signal	Pair Clear
	WDMX Unlock	On Off
Manual (see 6.7.2. Manual on page 23)	Red	000-255
	Green	000-255
	Blue	000-255
	White	000-255
	Amber	000-255
	UV	000-255
	Color Save	01-04
Frequency (see 6.7.3. Frequency on page 24)	600 Hz	
	1200 Hz	
	2000 Hz	
	4000 Hz	
	25000 Hz	
Auto (see 6.7.4. Auto on page 24)	Yes	
	No	
Program (see 6.7.5. Program on page 24)	Mode	01-32
	Color	01-05
	Speed	001-100
	Strobe	00-99
Slave (see 6.7.6. Slave on page 25)	Yes	
	No	
Working Time (see 6.7.7. Working Time on page 25)	OFF	
	1 hour	
	2 hours	
	3 hours	
	...	
	14 hours	
Settings (see 6.7.8. Settings on page 25)	Curves Select	Curve 1
		Curve 2
		Curve 3
		Curve 4
	Dimmer Speed	Fast
		Smooth
	Backlight Time	5 s
		10 s
		20 s
		30 s
		On
	DMX Fail	Off
		Hold
		Manual

Level 1	Level 2	Level 3
		Program
	IR	On Off
	Lock	On Off
	Factory Reset	Yes No
Information (see 6.7.9. Information on page 26)	Firmware version	
	Temperature	
	Operating humidity	
	Runmode	

6.7. Main Menu Options

The main menu has the following 9 options:

```

1: DMX
2: Manual
3: Frequency
4: Auto
5: Program
6: Slave
7: Working Time

```

```

DMX
Manual
Frequency
Auto
Program
Slave
Working Time

```

```

8: Settings
9: Information

```

```

Settings
Information

```

01) Press the **UP/DOWN** buttons to navigate through the main menu.

02) Press the **ENTER** button to open the submenus.

6.7.1. DMX

In this menu you can configure the DMX settings of the device.

```

DMX
1 Address: 001
2 Channels: 11
3 Signal:
4 WDMX Unlock:

```

01) Press the **UP/DOWN** buttons to scroll through the following 4 options:

- Address: Set DMX starting address of the device. The adjustment range is 001–512.
- Channels: Select the DMX channel mode: 6, 8 or 11 channels (see [6.9. DMX Channels](#) on page 29)
- Signal (see [6.7.1.1. Signal](#))
- WDMX Unlock (see [6.7.1.2. WDMX Unlock](#))


02) Press the **ENTER** button to confirm the selection and open the submenu.

6.7.1.1. Signal

In this submenu you can pair and unpair devices in a wireless master/slave setup.

To pair multiple devices in a wireless master/slave setup:


01) Open this submenu on the master device. The display reads Pair.



02) Press the **ENTER** button to pair the master device to the slave devices in the setup. During pairing the **wireless LED indicator (12)** blinks. When pairing is completed, the **wireless LED indicator (12)** lights up.

To unpair the devices in a wireless master/slave setup:

01) Open this submenu on the slave devices. The display reads Clear.



02) Press the **ENTER** button to unpair the slave devices in the setup. When unpairing is completed, the **wireless LED indicator (12)** turns off.

Note:

Once a slave device is paired to a master device in a wireless master/slave setup, the slave device remains paired to the master device. If you want to use the slave device in a different master/slave setup, you need to unpair the slave device from the first master device.

6.7.1.2. WDMX Unlock

In this submenu you can enable wireless DMX.

Press the **UP/DOWN** buttons to choose ON (to enable wireless DMX) or OFF (to disable wireless DMX). When you enable the wireless DMX, the **wireless LED indicator (12)** lights up.

6.7.2. Manual

In this menu you can create a custom color and save it.



01) Press the **UP/DOWN** buttons to select one of the 6 LED colors: red, green, blue, white, amber or UV.

02) Press the **ENTER** button to open the submenu.


03) Press the **UP/DOWN** buttons to set the intensity of the LEDs. The adjustment range is 0–255, from low to high intensity.

04) Repeat steps 1–3 to adjust the values for the rest of the LEDs to create any color.

- 05) Press the **UP/DOWN** buttons to select Color Save. Do this step and the following steps, if you want to save the color you created.
- 06) Press the **ENTER** button to open the submenu.
- 07) Press the **UP/DOWN** buttons to select one of the 4 available slots.
- 08) Press the **ENTER** button to confirm the selection. The display shows Save OK. The custom color created in steps 1–5 is saved on the selected slot.

6.7.3. Frequency

In this menu you can adjust the PWM (Pulse Width Modulation) frequency.



Press the **UP/DOWN** buttons to select the frequency: 600 Hz, 1200 Hz, 2000 Hz, 4000 Hz, or 25000 Hz.

6.7.4. Auto

In this menu you can activate auto mode.

Press the **UP/DOWN** buttons to choose YES (to play the built-in program in auto mode) or NO (to return to the previous screen).

6.7.5. Program


In this menu you can play a built-in program, adjust the speed of the built-in program, select a custom color, and add strobe effect.



- 01) Press the **UP/DOWN** buttons to select one of the 4 options:
 - Mode: Select one of the 32 built-in programs (01–32)
 - Color: Select one of the 4 custom colors (01–04) (see [6.7.2. Manual](#) on page 23). Position 05 in this submenu has no function
 - Speed: Adjust the speed of the built-in program. The adjustment range is 001–100, from slow to fast
 - Strobe: Add strobe effect. The adjustment range is 00–99, from low to high frequency. 00 is no strobe
- 02) Press the **ENTER** button to confirm the selection.

6.7.6. Slave

In this menu you can set the device as a slave device in a master/slave setup.




Press the **UP/DOWN** buttons to choose Yes (to set the device as a slave device) or No (to return to the previous screen).

Note:

In a master/slave setup, make sure that only one device is set to No (master device) and the remaining devices are set to Yes (slave devices).

6.7.7. Working Time

In this menu you can set the operating time of the device.



Press the **UP/DOWN** buttons to select the number of hours for which you want the device to remain in operation. The selection range is 1–14 hours, or OFF. If you select OFF, the device remains in operation until the battery is depleted.

6.7.8. Settings

In this menu you can adjust the settings of the device.



01) Press the **UP/DOWN** buttons to scroll through the following 7 options:

- Curves Select: Set the dimming curve. There are 4 options available: Curve 1, Curve 2, Curve 3 and Curve 4
- Dimmer Speed: Set the dimmer speed. There are 2 options available: Fast or Smooth
- Backlight Time: Set whether the backlight of the display remains on (On) or turns off after the selected amount of time: 5 s, 10 s, 20 s, or 30 s
- DMX Fail (see [6.7.8.1. DMX Fail](#))
- IR: Enable remote control mode: On/Off
- Lock (see [6.7.8.2. Lock](#))
- Factory Reset (see [6.7.8.3. Factory Reset](#))

02) Press the **ENTER** button to confirm the selection and open the submenu.

6.7.8.1. DMX Fail

In this submenu you can set the behavior of the device in case of a DMX failure.

Press the **UP/DOWN** buttons to select one of the 4 options:

- Off: The device will black out the output
- Hold: The device will use the last correctly received DMX signal
- Manual: The device will use the values selected in manual mode (see [6.7.2. Manual](#) on page 23)
- Program: The device will run the built-in program

6.7.8.2. Lock

In this submenu you can activate the display lock.

Press the **UP/DOWN** buttons to toggle between ON and OFF.

- ON: The display lock is on. The display is locked after the display turns off. To access the main menu, you need to enter the password. The default password is pressing and holding the **MENU** and the **DOWN** buttons at the same time for 3 s
- OFF: The access to the main menu remains unlocked after the display turns off

6.7.8.3. Factory Reset


In this submenu you can restore the default factory settings of the device.

Press the **UP/DOWN** buttons to toggle between Yes and No.

- Yes: Restore to default factory settings
- No: Keep the current settings of the device

6.7.9. Information

In this menu you can view the following parameters of the device: firmware version, LEDs temperature, operating hours of the device, current run mode and UID.

A black rectangular display showing the 'Information' menu. The title 'Information' is at the top in a large, light blue font. Below it, five lines of white text provide device details: 'Ver: V1.1', 'Temp 22°C', 'Oper H: 0000 H', 'Run Mode: Mode', and 'UID: 000000000000'.

Information
Ver: V1.1
Temp 22°C
Oper H: 0000 H
Run Mode: Mode
UID: 000000000000

Note:

This device does not support RDM. The displayed UID number is an example.

6.8. Remote Control

The device can be operated with an IR remote control. The remote control is not included in the delivery (see [3.5. Optional Accessories](#) on page 10).



DANGER
Do not ingest battery, chemical burn hazard.

The remote control contains a coin cell battery. If the coin cell battery is swallowed, it can cause severe internal burns in just 2 hours and can lead to death.

6.8.1. Remote Control Mode


To control the device with the IR remote control:

- 01) Activate remote control mode in the Settings menu (see [6.7.8. Settings](#) on page 25).
- 02) Point the IR remote control to the **IR sensor (03)** and use the buttons on the IR remote control to control the device (see [6.8.2. Functions of the Remote Control Buttons](#) on page 28). Make sure that you point the IR remote control in the range of the **IR sensor (03)**.


Note:

You can control several devices at the same time with the IR remote control.

Figure 13



6.8.2. Functions of the Remote Control Buttons



Button Description Function

ON/OFF	ON/OFF	Turns the LEDs on/off
▲	Up	Increases the value
▼	Down	Decreases the value
Auto	Auto	Auto mode
Sound	Sound	No function
Strob	Strobe	Selects a built-in program and adds strobe effect

Button	Description	Function
Speed	Speed	Speed adjustment of the built-in programs
M/S	Master/Slave	Sets the device as a master or a slave
Fade	Fade	Color flow
Add	Address	Sets the DMX starting address and selects the DMX channel mode
Full	Full	Full-on light output
Eco	Economical	Economical mode (80 % efficiency) or Normal mode (100 % efficiency)
Red	Red	Activates the red LEDs
Green	Green	Activates the green LEDs
Blue	Blue	Activates the blue LEDs
White	White	Activates the white LEDs
Amber	Amber	Activates the amber LEDs
UV	UV	Activates the UV LEDs
Org	Orange	Activates the orange color
Cyan	Cyan	Activates the cyan color
Pink	Pink	Activates the pink color

6.9. DMX Channels

6 CH	8 CH	11 CH	Function	Value	Setting
	1	1	Dimming	000–255	From low to high intensity (0–100 %)
	2	2	Strobe	000–010	No function
				011–255	From low to high frequency
1	3	3	Red	000–255	From low to high intensity (0–100 %)
2	4	4	Green	000–255	From low to high intensity (0–100 %)
3	5	5	Blue	000–255	From low to high intensity (0–100 %)
4	6	6	White	000–255	From low to high intensity (0–100 %)
5	7	7	Amber	000–255	From low to high intensity (0–100 %)
6	8	8	UV	000–255	From low to high intensity (0–100 %)
				000–010	No function
				011–030	R: 100 % G: 0–100 % B: 0
				031–050	R: 100–0 % G: 100 % B: 0
				051–070	R: 0 G: 100 % B: 0–100 %
				071–090	R: 0 G: 100–0 % B: 100 %
				091–110	R: 0–100 % G: 0 B: 100 %
				111–130	R: 100 % G: 0 B: 100–0 %
				131–150	R: 100 % G: 0–100 % B: 0–100 %
				151–170	R: 100–0 % G: 100–0 % B: 100 %
				171–200	R: 100 % G: 100 % B: 100 %
		9	Color macros and white balance	201–205	White 1
				206–210	White 2
				211–215	White 3
				216–220	White 4
				221–225	White 5
				226–230	White 6
				231–235	White 7
				236–240	White 8
				241–245	White 9
				246–250	White 10
				251–255	White 11
				000–010	No function
				011–040	RGB color mixing
				041–070	CMY color mixing
				071–100	RGBA color mixing
				101–130	RGBACMY color mixing
				131–160	RGB color changing
				161–190	CMY color changing
				191–220	RGBA color changing
				221–255	RGBACMY color changing
		10	Auto run		
		11	Auto speed	000–255	From slow to fast

7. Troubleshooting

This troubleshooting guide contains solutions to problems which can be carried out by an ordinary person. The device does not contain user-serviceable parts.

Unauthorized modifications to the device will render the warranty void. Such modifications may result in injuries and material damage.

Refer servicing to instructed or skilled persons. Contact your Highlite International dealer in case the solution is not described in the table.

Problem	Probable cause(s)	Solution
The device does not turn on	The battery is depleted	Recharge the battery (see 4.5. Charging the Battery on page 13)
The device does not respond to the IR remote control	The IR remote control is outside of the range of the IR sensor	Walk closer to the device or change the angle at which you point the IR remote control to the device (see 6.8.1. Remote Control Mode on page 27)
	The battery in the IR remote control is depleted	Change the battery of the IR remote control
The device does not respond to DMX control	The remote control mode is not enabled on the device	Enable remote control mode (see 6.7.8. Settings on page 25)
	The controller is not connected	Connect the controller
The device responds erratically to DMX control	The signal is reversed. The 3-pin DMX OUT of the controller does not match the DMX IN of the device	Install a phase-reversing cable between the controller and the device
	The controller is defective	Use a different controller
The device responds erratically to DMX control	Connections are defective	Examine connections and cables. Correct defective connections. Repair or replace damaged cables
	The data link is not terminated with a 120 Ω termination plug	Insert a termination plug in the DMX OUT connector of the last device on the link
The device does not respond to wireless control	Incorrect addressing	Make sure that the address settings are correct
	In case of a setup with multiple devices, one of the devices is defective and disturbs data transmission on the link	To find out the defective device, bypass one device at a time until normal operation is restored
The device does not respond to wireless control	The device is not paired. The wireless LED indicator (12) is off.	Verify the settings of the device (see 5.3. Wireless Connection on page 17)
	The slave device is paired to a different master device. The wireless LED indicator (12) is on.	Unpair the slave device and pair it to the current master device (see 6.7.1.1. Signal on page 23)
No light or LEDs cut out intermittently	The device is not in the range of the wireless transmitter	Make sure that there is a clear line of sight between all devices in the wireless setup (see 5.3. Wireless Connection on page 17)
	The controller or the transmitter (transceiver) of the controller is defective	Use a different controller
No light or LEDs cut out intermittently	LEDs are damaged	Turn off the device. Contact your Highlite International dealer

8. Maintenance

8.1. Preventive Maintenance

**Attention**

Before each use, examine the device visually for any defects.

Make sure that:

- All screws used for installing the device or parts of the device are tightly fastened and are not corroded.
- The safety devices are not damaged.
- There are no deformations on housings, fixings and installation points.
- The lens is not cracked or damaged.
- The power cables are not damaged and do not show any material fatigue.

8.1.1. Basic Cleaning Instructions

The external lens of the device must be cleaned periodically in order to optimize the light output. The cleaning schedule depends on the conditions at the site where the device is installed. When smoke or fog machines are used at the site, the device will need more frequent cleaning. On the other hand, if the device is installed in well-ventilated area, it will need less frequent cleaning. To establish a cleaning schedule, examine the device at regular intervals during the first 100 hours of operation.

To clean the device, follow the steps below:

- 01) Disconnect the device from the electrical power supply.
- 02) Allow the device to cool down for at least 15 minutes.
- 03) Remove the dust collected on the external surface with dry compressed air and a soft brush.
- 04) Clean the lens with a damp cloth. Use a mild detergent solution.
- 05) Dry the lens carefully with a lint-free cloth.
- 06) Clean the connectors with a damp cloth.

**Attention**

- Do not immerse the device in liquid.
- Do not use alcohol or solvents.
- Make sure that the connectors are fully dry before using them.

8.2. Corrective Maintenance

The device does not contain user-serviceable parts. Do not open the device and do not modify the device.

Refer repairs and servicing to instructed or skilled persons. Contact your Highlite International dealer for more information.

9. Deinstallation, Transportation and Storage

9.1. Instructions for Deinstallation

**WARNING**

Incorrect deinstallation can cause serious injuries and damage of property.

- Always observe the national and site-specific regulations during deinstallation and derigging of the device.
- Wear personal protective equipment in compliance with the national and site-specific regulations.

9.2. Instructions for Transportation

This device contains a rechargeable (secondary) lithium-ion battery. Lithium-ion batteries contained in equipment fall under the category of dangerous goods for transportation.

- Make sure that you are in compliance with all applicable transportation regulations when you transport the device.
- Use the original packaging to transport the device or other suitable packaging that complies with the regulations for transportation of secondary lithium-ion batteries.

9.3. Storage

This device contains a rechargeable (secondary) lithium-ion battery. The battery is not replaceable. The battery may explode or cause burns if it is crushed, disassembled or exposed to fire or high temperatures.

- Store the device in a dry place, at temperatures between 5 and 20 °C. Lithium-ion batteries self-discharge during storage. Temperatures above 20 °C speed up the self-discharging process.
- Do not store the device with depleted battery. Make sure that the battery is charged to at least 50 % before storing the device.
- If the device is stored for an extended period, check regularly the state of charge of the battery (see [4.5. Charging the Battery](#) on page 13).
- Clean the device before storing (see [8.1.1. Basic Cleaning Instructions](#) on page 31).
- Store the device in the original packaging, if possible.

10. Disposal

This device contains a lithium-ion battery. Do not dispose of with the household waste.

Correct disposal of this product



Waste Electrical and Electronic Equipment

This symbol on the product, its packaging or documents indicates that the product shall not be treated as household waste. Dispose of this product by handing it to the respective collection point for recycling of electrical and electronic equipment. This is to avoid environmental damage or personal injury due to uncontrolled waste disposal. For more detailed information about recycling of this product contact the local authorities or the authorized dealer.

11. Approval



Hereby, Highlite International declares that the device EventLITE 4/10 Q6, product code 44067, is in compliance with Directive 2014/53/EU (RED – Radio Equipment Directive).

The full text of the EU declaration of conformity is available on the respective product page on the website of Highlite International (www.highlite.com).

